

USB-DIO96H/50

Specifications



**MEASUREMENT
COMPUTING™**

Document Revision 2.1, February, 2010
© Copyright 2010, Measurement Computing Corporation

Specifications

This specification applies to revision 2 hardware and later

This specification covers revision 2 of the USB-DIO96H/50 hardware, which uses a 5 V power supply. Revision 1 of the USB-DIO96H/50 hardware was designed with a 9 V power supply and daisy chained hub. For revision 1 hardware specifications, refer to www.mccdaq.com/PDFs/specs/USB-DIO96H-50_R1-spec.pdf.

Typical for 25 °C unless otherwise specified.

Specifications in *italic text* are guaranteed by design.

Digital input/output

Table 1. Digital I/O specifications

| | |
|----------------------------|--|
| Output | 74ABT244A |
| Input | 74ACT373 |
| Configuration | Eight banks of 8, eight banks of 4, programmable by bank as input or output |
| Pull-up/pull-down | High impedance pull-up/pull -down selectable via DIP switch for each digital input port. |
| Number of I/O | 96 |
| Output high | 2.0 V minimum @ -24 mA |
| Output low | 0.5 V maximum @ 64 mA |
| Input high | 2.0 V minimum, 5.5 V maximum |
| Input low | 0.8 V maximum, -0.5 V absolute minimum |
| Input impedance | 47 kΩ (series resistance) |
| Source current | Maximum = 24 mA per output |
| Sink current | Maximum = 64 mA per output |
| Power up/reset state | Input mode |
| Debounce mode | Debouncing option available through firmware that samples all inputs eight times over a specified interval and latches out the input state only when eight consecutive samples are identical (all 0s or all 1s). Available debouncing intervals are 1 ms, 2 ms, 5 ms, 10 ms, 20 ms, 50 ms, 100 ms, 200 ms, and 400 ms. |
| Debounce interval accuracy | +0% / -12.5% |

Power

Table 2. Power specifications

| Parameter | Conditions | Specification |
|-----------------------------------|--|---|
| USB +5 V input voltage range | | 4.75 V minimum to 5.25 V maximum |
| USB +5 V supply current | All modes of operation | <100 mA |
| External power input (Note 1) | | 5 VDC ± 5% (5 VDC power supply provided) |
| External power supply (included) | MCC p/n PS-5V3AEPS | 5 VDC, 15 W, 5% regulation |
| Alternate external power supply | From PC auxiliary power (cable not included) | Jumper selectable Molex® connector internal to case |
| Voltage supervisor limits | 4.13 V > V _{ext} or V _{ext} > 5.59 V | PWR LED = Off (power fault) |
| | 4.13 V < V _{ext} < 5.59 V | PWR LED = On |
| Power supply current | | 2.7 A maximum |
| User 5 V output voltage range | Available at +5 V pins | 4.0 V minimum, 5.25 V maximum |
| User 5 V output current available | Total from all +5 V pins | 50 mA maximum |

Note 1: Voltage specification applies at barrel plug power input. The power supply provided with the board meets this specification at the rated total power supply current. If a different power supply is used, small line resistances could cause significant voltage drop between the power supply and the barrel plug input.

Environmental

Table 3. Environmental specifications

| | |
|------------------------------------|--------------------------------|
| <i>Operating temperature range</i> | <i>0 to 60 °C</i> |
| <i>Storage temperature range</i> | <i>-40 to 85 °C</i> |
| <i>Humidity</i> | <i>0 to 90% non-condensing</i> |

USB specifications

Table 4. USB specifications

| | |
|----------------------|---|
| USB "B" connector | Input |
| USB device type | USB 2.0 (full-speed) |
| Device compatibility | USB 1.1, USB 2.0 |
| USB cable type | <i>A-B cable, UL type AWM 2527 or equivalent. (minimum 24 AWG VBUS/GND, minimum 28 AWG D+/D-)</i> |
| USB cable length | 3 meters maximum |

Data transfer rates

Table 5. Data transfer rate specifications

| | |
|---|---|
| Digital I/O transfer rates (software paced) | System-dependent, 33 to 250 port reads/writes or single-bit reads/writes per second typical |
|---|---|

Mechanical

Table 6. Mechanical specifications

| | |
|----------------------|---|
| Card dimensions | 304.8 mm (L) x 121.9 mm (W) x 20.0 mm (H) |
| | 12.0" (L) x 4.8" (W) x 0.8" (H) |
| Enclosure dimensions | 342.9 mm (L) x 125.7 mm (W) x 58.9 mm (H) |
| | 13.50" (L) x 4.95" (W) x 2.32" (H) |

Main connectors and pin out

Table 7. Ribbon connector specifications

| | |
|-------------------------------|---|
| Connectors | P1-P2: 50-pin 0.1" IDC type box header |
| Compatible cables | C-50FF-x, 50-pin ribbon cable |
| Compatible accessory products | SCB-50 CIO-MINI50 (2) CIO-TERM100 CIO-SPADE50 (2) CIO-ERB24 CIO-SERB24/FD CIO-ERB48 CIO-SERB48 SSR-RACK24 SSR-RACK48 |

P1

Table 8. P1 pin out

| Pin | Signal name | Pin | Signal name |
|-----|-------------------|-----|-------------------|
| 50 | GND | 49 | +5V |
| 48 | FIRSTPORTC Bit 0 | 47 | FIRSTPORTC Bit 1 |
| 46 | FIRSTPORTC Bit 2 | 45 | FIRSTPORTC Bit 3 |
| 44 | FIRSTPORTC Bit 4 | 43 | FIRSTPORTC Bit 5 |
| 42 | FIRSTPORTC Bit 6 | 41 | FIRSTPORTC Bit 7 |
| 40 | FIRSTPORTB Bit 0 | 39 | FIRSTPORTB Bit 1 |
| 38 | FIRSTPORTB Bit 2 | 37 | FIRSTPORTB Bit 3 |
| 36 | FIRSTPORTB Bit 4 | 35 | FIRSTPORTB Bit 5 |
| 34 | FIRSTPORTB Bit 6 | 33 | FIRSTPORTB Bit 7 |
| 32 | FIRSTPORTA Bit 0 | 31 | FIRSTPORTA Bit 1 |
| 30 | FIRSTPORTA Bit 2 | 29 | FIRSTPORTA Bit 3 |
| 28 | FIRSTPORTA Bit 4 | 27 | FIRSTPORTA Bit 5 |
| 26 | FIRSTPORTA Bit 6 | 25 | FIRSTPORTA Bit 7 |
| 24 | SECONDPORTC Bit 0 | 23 | SECONDPORTC Bit 1 |
| 22 | SECONDPORTC Bit 2 | 21 | SECONDPORTC Bit 3 |
| 20 | SECONDPORTC Bit 4 | 19 | SECONDPORTC Bit 5 |
| 18 | SECONDPORTC Bit 6 | 17 | SECONDPORTC Bit 7 |
| 16 | SECONDPORTB Bit 0 | 15 | SECONDPORTB Bit 1 |
| 14 | SECONDPORTB Bit 2 | 13 | SECONDPORTB Bit 3 |
| 12 | SECONDPORTB Bit 4 | 11 | SECONDPORTB Bit 5 |
| 10 | SECONDPORTB Bit 6 | 9 | SECONDPORTB Bit 7 |
| 8 | SECONDPORTA Bit 0 | 7 | SECONDPORTA Bit 1 |
| 6 | SECONDPORTA Bit 2 | 5 | SECONDPORTA Bit 3 |
| 4 | SECONDPORTA Bit 4 | 3 | SECONDPORTA Bit 5 |
| 2 | SECONDPORTA Bit 6 | 1 | SECONDPORTA Bit 7 |

P2

Table 9. P2 pin out

| Pin | Signal name | Pin | Signal name |
|-----|------------------|-----|------------------|
| 100 | GND | 99 | +5V |
| 98 | THIRDPORC Bit 0 | 97 | THIRDPORC Bit 1 |
| 96 | THIRDPORC Bit 2 | 95 | THIRDPORC Bit 3 |
| 94 | THIRDPORC Bit 4 | 93 | THIRDPORC Bit 5 |
| 92 | THIRDPORC Bit 6 | 91 | THIRDPORC Bit 7 |
| 90 | THIRDPORB Bit 0 | 89 | THIRDPORB Bit 1 |
| 88 | THIRDPORB Bit 2 | 87 | THIRDPORB Bit 3 |
| 86 | THIRDPORB Bit 4 | 85 | THIRDPORB Bit 5 |
| 84 | THIRDPORB Bit 6 | 83 | THIRDPORB Bit 7 |
| 82 | THIRDPORA Bit 0 | 81 | THIRDPORA Bit 1 |
| 80 | THIRDPORA Bit 2 | 79 | THIRDPORA Bit 3 |
| 78 | THIRDPORA Bit 4 | 77 | THIRDPORA Bit 5 |
| 76 | THIRDPORA Bit 6 | 75 | THIRDPORA Bit 7 |
| 74 | FOURTHPORC Bit 0 | 73 | FOURTHPORC Bit 1 |
| 72 | FOURTHPORC Bit 2 | 71 | FOURTHPORC Bit 3 |
| 70 | FOURTHPORC Bit 4 | 69 | FOURTHPORC Bit 5 |
| 68 | FOURTHPORC Bit 6 | 67 | FOURTHPORC Bit 7 |
| 66 | FOURTHPORB Bit 0 | 65 | FOURTHPORB Bit 1 |
| 64 | FOURTHPORB Bit 2 | 63 | FOURTHPORB Bit 3 |
| 62 | FOURTHPORB Bit 4 | 61 | FOURTHPORB Bit 5 |
| 60 | FOURTHPORB Bit 6 | 59 | FOURTHPORB Bit 7 |
| 58 | FOURTHPORA Bit 0 | 57 | FOURTHPORA Bit 1 |
| 56 | FOURTHPORA Bit 2 | 55 | FOURTHPORA Bit 3 |
| 54 | FOURTHPORA Bit 4 | 53 | FOURTHPORA Bit 5 |
| 52 | FOURTHPORA Bit 6 | 51 | FOURTHPORA Bit 7 |

Measurement Computing Corporation
10 Commerce Way
Suite 1008
Norton, Massachusetts 02766
(508) 946-5100
Fax: (508) 946-9500
E-mail: info@mccdaq.com
www.mccdaq.com