

# SPECIFICATIONS

## PC104-DAS08

Analog Input & Digital I/O



Revision 4, October, 2001

© Copyright 2001, MEASUREMENT COMPUTING CORPORATION

## SPECIFICATIONS

---

---

Power Consumption	
+5V:	130 mA typical, 185 mA max
+12V:	18 mA typical, 25 mA max
-12V:	12 mA typical, 18 mA max
<hr/>	
Analog Input Section	
A/D converter type	AD674
Resolution	12 bits
Number of channels	8, single-ended
Input Ranges	$\pm 10V$ , $\pm 5V$ , 0 to $+10V$ , switch selectable
Polarity	Unipolar/Bipolar, switch selectable
A/D pacing	Internal counter or external source (Interrupt Input, jumper selectable, rising edge) or software polled
A/D Trigger sources	External polled gate trigger (Digital In 1)
Data transfer	Interrupt or software polled
DMA	None
A/D conversion time	15 $\mu s$
Throughput	20 kHz, PC dependent
Accuracy	$\pm 0.01\%$ of reading $\pm 1$ LSB
Differential Linearity error	$\pm 1$ LSB
Integral Linearity error	$\pm 0.5$ LSB
No missing codes guaranteed	12 bits
Gain drift (A/D specs)	$\pm 25$ ppm/ $^{\circ}C$
Zero drift (A/D specs)	$\pm 10\mu V/^{\circ}C$
Common Mode Range	$\pm 10V$
CMRR	72 dB
Input leakage current (@25° C)	100 nA
Input impedance	10 MegOhms min
Absolute maximum input voltage	$\pm 35V$

**Digital Input / Output****Digital Type (Main connector)**

Output:	74LS273
Input:	74LS244
Configuration	4 fixed output bits, 3 fixed input bits
Number of channels	4 out, 3 in
Output High	2.7 volts min @ -0.4 mA
Output Low	0.4 volts max @ 8 mA
Input High	2.0 volts min, 7 volts absolute max
Input Low	0.8 volts max, -0.5 volts absolute min
Output power-up / reset state	
Interrupts	2 thru 7, jumper-selectable
Interrupt enable	Programmable
Interrupt sources	External (Interrupt In), rising edge

**Counter Section****Counter type**

82C54

**Configuration**

3 down-counters, 16 bits each

Counter 0 - independent, user configurable

Source: user connector (Counter 0 In)

Gate: user connector (Gate 0)

Output: user connector (Counter 0 Out)

Counter 1 - independent, user configurable

Source: user connector (Counter 1 In)

Gate: user connector (Gate 1)

Output: user connector (Counter 1 Out)

Counter 2 - independent, user configurable

Source: PC SysClk via divide by 2 circuit

Gate: user connector (Gate 2)

Output: user connector (Counter 2 Out)

Clock input frequency

10 MHz max

High pulse width (clock input)

30 ns min

Low pulse width (clock input)

50 ns min

Gate width high

50 ns min

Gate width low

50 ns min

Input low voltage

0.8V max

Input high voltage

2.0V min

Output low voltage

0.4V max

Output high voltage

3.0V min

**Environmental**

Operating temperature range

0 to 50°C

Storage temperature range

-20 to 70°C

Humidity

0 to 90% non-condensing

**Measurement Computing Corporation****10 Commerce Way****Suite 1008****Norton, Massachusetts 02766****(508) 946-5100****Fax: (508) 946-9500****E-mail: [info@mccdaq.com](mailto:info@mccdaq.com)****[www.mccdaq.com](http://www.mccdaq.com)**